Real-Time Digital Signal Processing of Component-Oriented Phased Array Radars*

Chin-Fu Kuo, Tei-Wei Kuo, and Cheng Chang[†]

Department of Computer Science and Information Engineering

National Taiwan University, Taipei, Taiwan 106, ROC

[†]Phased Array Radar Section, Electronic System Division

Chung Shan Institute of Science and Technology

Lung-Tan, Taiwan 325, ROC

Abstract

With the advance of hardware and software technology, modern phased array radars are now built with commercial-off-the-shelf (COTS) components, and it opens up a new era in real-time resource scheduling of digital signal processing. This paper targets the essential issues in building component-oriented Signal Processor (SP), which is one of the two major modules in modern phased array radars. We propose a simple but effective task allocation policy and a real-time scheduling algorithm to address the design objectives of SP's. We are able to bound the number of processing units needed for a component-oriented SP in the design time, while everything was done empirically in the past. A series of experiments were done to demonstrate the strength of our methodology.

1 Introduction

A phased array radar must search and track suspicious targets in its surveillance space in a real-time fashion. There are two major modules in a phased array radar: Radar Control Computer (RCC) and Signal Processor (SP). RCC is responsible to scheduling radar beam transmissions for search and tracking based on targets' status and search types. On the other hand, SP must process returned signals in a real-time fashion. Although the design of a phased array radar must meet various real-time requirements, it is often designed with non-real-time resource scheduling mechanisms, such as FIFO scheduling [1]. The common reason in doing so is mainly because of hardware constraints and insufficient knowledge of real-time technology. As a result,

much resource is wasted with a very limited guarantee on system performance.

The development of component-oriented SP's is strongly influenced by the Rapid prototyping of Application Specific Signal Processors (RASSP) program lead by the Department of Defense, United States of America [17]. The RASSP program formalized an engineering process for developing SP's to reduce the total product development time and cost by a factor of four. While a number of researchers have proposed highly efficient real-time scheduling algorithms, e.g., [12, 13, 19, 10, 11], little work is done for radar scheduling. The task models and the work presented in [2, 5, 7, 10, 11] are among the few closely related to dwell scheduling at the RCC level¹. The work presented in this paper is one of the first attempts in building a truly real-time SP. The traditional scheduling approaches for signal processing in SP's are merely FIFO-like mechanisms which may let the signal processing seriously suffer from the priority inversion problem and under-utilize the processing power of processing units. With virtually everything done and verified empirically in the traditional approaches, the system capacity of a traditional SP is usually hard to estimate or estimated very conservatively.

This paper addresses two major issues in the design of SP's: (1) the schedulability of critical tasks under the minimum operation requirements, such as the processing of search signals. (2) the system capacity estimation. In this paper, we propose a simple but effective task allocation policy, which separates periodic

*Supported in part by a research grant from the Chung Shan Institute of Science and Technology and a research grant from the National Science Council under Grant NSC89-2213-E-194-011.

¹Note that although researchers have explored the scheduling of SDF graphs for the SAR benchmark and other related signal processing applications in the embedded systems and signal processing literature, the graph processing models are not directly related to real-time scheduling in SP's, where SDF is the dataflow language used in the RASSP program and more related to RCC-level workloads.

and aperiodic workloads, and a real-time scheduling algorithm to process digital signals in a real-time fashion. We derive bounds for the number of processing units needed for a SP under performance specifications. Most importantly, we formalize the workload of a typical component-oriented SP for modern phased array radars. We must emphasize that this work represents one of the pioneer work in building the next-generation SP's. In the past, virtually everything was done empirically. Inefficient resource allocation mechanisms like FIFO were adopted, and system capacity was very difficult to estimate. Currently, we are building a SP prototype for the next-generation radar systems.

The rest of this paper is organized as follows: Section 2 defines the system architecture of a typical SP and illustrates the idea of component-oriented SP's and radars. Section 3 formally defines the workload of a typical SP. Section 4 proposes our task allocation policy and real-time scheduling algorithm. We also propose bounds for the number of processing units needed for a SP under performance specifications. Section 5 provides experimental results to show the strength of our approach. Section 6 is the conclusion.

2 System Architecture

Figure 1: The hardware architecture of a phased array radar

A phased array radar consists of several important modules: Radar Control Computer (RCC), Signal Processor (SP), Beam Steering Controller (BSC), Receiver, Antenna, and Transmitter, where a SP consists of an Analog Signal Processor (ASP), a Signal Processing Computer (SPC), and various processing units, as shown in Figure 1 [1, 7, 15, 18]. RCC schedules dwell transmissions in a real-time fashion by sending SPC commands. When SPC receives commands from RCC for radar beam transmissions, it issues commands to

BSC and Transmitter for radar beam transmissions in specified directions. When Antenna and Receiver receive returned signals and pass them to ASP for analog-to-digital signal processing. The digital signals are saved at the input buffer unit (IBU) for later processing. Processing units of a SP includes several types of processors, such as those for data processing, pulse compression, digital signal processing, etc, which are Vector Signal Processors (VSP) in the following paragraphs. Data Interconnection Network (DIN) is for data transmission between processing units and IBU. All processing units, IBU, and DIN are under the command of SPC, where SPC assigns each processing unit a signal processing job to meet the hard deadline of each individual job. Commands in a SP go through another channel, such as VMEbus or Fibre Channel.

Figure 2: A component-oriented signal processor

With the advance of software and hardware technology, a modern radar SP is no longer a complicated hardware system with everything wired. Instead, a SP can be made of many commercial-off-the-shelf (COTS) components, and the functions of many hardware components are now re-implemented by software algorithms [3]. A SP can be considered as a collection of internal nodes, as shown in Figure 2, where an internal node (IN) can be an ASP, any COTS board (i.e., VSP) with multiple digital signal processors (DSP's), such as ADSP 21060 DSP's, or memory modules for IBU.

The interconnection fabrics are communication channels for data and command delivery. Network bridges can connect different groups of SP and related subsystems which work together. Various radar digital signal processing functions, such as pulse doppler processing (PDP), moving target indication (MTI), tracking processing, and monopulse estimation, are implemented by software modules executed on VSP's, where each VSP may also be equipped with some special purpose processing units for time-consuming functions. Most importantly, different combinations of COTS replaceable VSP's may result in different SP's which may fit different radar system requirements. Also, as more powerful COTS DSP boards appear, a new SP can be built rapidly by using them.

3 Workload Characteristics

In phased array radars, RCC schedule radar-dwells in units called *scheduling interval* (SI) [1, 5, 8], where the length of scheduling interval is determined by various factors from the system specs and usually in tens-of-milliseconds. In the beginning of each scheduling interval, SPC receives commands from RCC, where the commands are dwell transmissions and their returned signal processing. SPC, which is in charge of the real-time resource scheduling of the entire SP, must issue commands to BSC and Transmitter for radar beam transmissions in specified directions and prepare to schedule the processing of returned signals in a real-time fashion. In this paper, we will focus on the real-time processing of returned signals, which is the main duty of a SP. For the simplicity of presentation, we will use terms "task", "job", and "dwell" interchangeably.

The incoming workload of a SP in each i_{th} SI can be formally defined as a collection of tasks $T_i = \{\tau_{i,1}, \tau_{i,2}, \dots, \tau_{i,n_i}\}$, where each task $\tau_{i,j}$ is associated with three parameters $(r_{i,j}, c_{i,j}, d_{i,j})$. $r_{i,j}$, $c_{i,j}$, and $d_{i,j}$ are the ready time, the processing time, and the deadline of the returned signal for the corresponding dwell, i.e., $\tau_{i,j}$, issued in the i_{th} SI, respectively. Each task $\tau_{i,j}$ is assigned to a VSP to execute (or process) non-preemptively. In other words, once a task is assigned to execute on a VSP, the VSP is no longer available until the task is done. The processing time $c_{i,j}$ of task $\tau_{i,j}$ includes the actual processing time of the corresponding signal and the data and command communication time.

We are interested in a homogeneous SP environment, in which there are N identical VSP's, and each internal node is a COTS DSP board. The types of tasks in a phased-array-radar SP can be, in general, classified as search, track, and confirmation tasks [1, 2, 5, 9]: Search tasks are periodic tasks (issued by RCC), which periodically search moving objects in different directions and elevation, such as the Horizontal Search and Volumetric Search [2]. Track tasks, which are used to track interesting objects, i.e., targets, in the surveillance space (by RCC), can be considered as aperiodic tasks because their periods may change frequently, depending on the target type, target position, target speed, system load, etc [1, 2]. Search tasks may trigger the creation of track tasks on RCC through confirmation tasks. In other words, when suspicious targets are identified by search tasks on RCC, a confirmation task is created for each suspicious target. If a suspicious target is identified as a real target, the corresponding confirmation task is removed, and a corresponding track task is created [1, 2]. In other words, confirmation tasks are also aperiodic. Note that the precedence constraints of tasks

Tasks	Timing Parameters	Periodic
Search	$\{R, C_s, (SD \cdot SI), Max, Min, K, P\}$	Yes
Track	$(r_{i,j}, C_t, d_{i,j})$	No
Confirmation	$(r_{i,j}, C_c, d_{i,j})$	No

Table 1: SP workload characteristics

is handled at the RCC level. At the SP level, only independent non-preemptive tasks are observed.

With similar signal processing procedures, the processing time of each search task can be well bounded as a constant C_s . Because of the same reason, track tasks (/confirmation tasks) also have a bounded processing time C_t ($/C_c$) [7]. The deadlines of search, confirmation, and track tasks are a multiple of a SI because RCC and SP communicate with each other at a fixed and specified point of each SI [1, 5]. In this paper, we consider a high performance SP which might have many track (/confirmation) tasks whose deadlines are as close as the twice of SI, and search tasks can be pushed to their extreme such that their deadlines might be close to a threshold value equal to SD times of SI. Furthermore, the search tasks in many phased array radars often have a common big cycle such that all of the search tasks in the system can be considered as a single search multiframe-like task [1, 7], where the execution time of a multiframe task varies regularly in consecutive periods [14]. Such an integrated single search task can be, in general, modeled (and well bounded) by the following seven parameters:

$$\tau^{search} = \{R, C_s, (SD \cdot SI), Max, Min, K, P\}$$

where in the first K periods, the search task will request Max identical non-preemptive jobs, and each of them is of the size C_s . Starting from the $(K + 1)$ period until the P_{th} period, the search task will request Min non-preemptive jobs ($Min < Max$), and each of them is of the size C_s . The search task repeats for each P periods, where each P periods is called a *big cycle*. The relative deadline of each non-preemptive job is $(SD \cdot SI)$ (from the beginning of its issuing SI). When there are x non-preemptive jobs $J_1, J_2, \dots, J_x$ issued in a period, the ready time of the i_{th} job is set as $(R \cdot i)$. It is because there is only one transmitter, receiver, and ASP such that signals are returned one after another. The first K periods of the search task is called the *peak duration*. The workload of a SP is summarized in Table 1.

4 Real-Time Scheduling of Digital Signal Processing - A Case Study

4.1 Overview

The FIFO scheduling policy adopted in many traditional SP's may not be suitable to an advanced component-oriented SP because many hardware functions are no longer hardwired. The re-implementation of hardware functions in terms of software modules makes a highly flexible system architecture possible. Constraints on (FIFO) data flow in many traditional SP's can be substantially relaxed. In this paper, we will present our approach in building a modern real-time SP with a performance guarantee.

A phased array radar must guarantee the minimum operation of the system which is often realized by periodic tasks responsible of searching suspicious targets in the surveillance space [1, 7]. As a result, for each scheduling interval (SI), RCC usually sends SPC a queue of tasks where the jobs of the search task are left in front of other tasks. The traditional FIFO scheduling policy unavoidably suffers from serious priority inversion problems for the jobs of the search task, where priority inversion is a phenomenon in which a higher priority task is blocked by a lower priority task. It is because track tasks which are not processed in the previous SI might be scheduled before the new jobs of the search task according to the FIFO scheduling policy. If there is a burst of track tasks coming in the previous SI's, jobs of the search task may miss their hard deadlines unless a lot of processing units are deployed in the SP. Furthermore, the mixed scheduling of the search task, track tasks, and confirmation tasks also incurs great difficulty in analyzing the timing behavior of the system and in deriving the capability of the SP system with a specified configuration. It is because the arrivals of track and confirmation tasks are highly dynamic. In other words, a hard-real-time SP system under the traditional approach is very difficult to verify its performance specifications. With its performance usually being verified empirically, engineers are forced to dump much more processing units than what they actually need.

The purpose of this section is to first present a simple but effective task allocation policy in a typical component-oriented SP, which shows some useful properties, and then apply the earliest deadline first (EDF) algorithm [12] in a three level priority scheduling framework to schedule SP jobs in a real-time fashion. The rationale behind of the separated EDF scheduling is to reflect the semantic importance of different tasks. Note that traditional FIFO scheduling policy cannot distin-

	R	$(SD \cdot SI)$	Max	Min	K	P
Parameters	0	$3SI$	3	1	3	6

Table 2: Timing parameters of an example search task

guish the importance of different jobs. We will then propose formula for radar engineers to derive the number of VSP's possibly needed for a radar SP.

4.2 Real-Time Task Allocation and Scheduling Strategy

4.2.1 Task Allocation Policy - a Rule of Thumb

In a component-oriented SP, the processing time C_s of each non-preemptive job of the search task can be much more than the length of a SI. On the other hand, the processing time of a track or confirmation task is much less than a SI. The relative deadline of track and confirmation tasks can be as close as $2SI$, while the relative deadline of the search task can be close to its big cycle, which is often much more than $2SI$. As a result, the number of VSP's in a SP is often more than the number of jobs issued by the search task in each SI during its peak duration.

Figure 3: The execution of the jobs issued by the search task when the jobs may run on all VSP's, and $C_s = 1\frac{1}{2}SI$.

The task allocation policy is motivated by the following observation: Suppose that there are 3 jobs issued by the search task in each SI during its peak duration. Let the system consist of 5 VSP's, and the ready time R of each job of the search task be zero (similar observation can be obtained even if R is nonzero). Assume that each job of the search task needs $C_s = 1\frac{1}{2}SI$ amount of processing time, as shown in Table 2.

Figure 3 shows the executions of the jobs issued by the search task, where the search task has a higher priority than other tasks, and a priority-driven scheduling policy is adopted. The jobs issued by the search task at the i th SI are marked by "i". Since the relative deadline of track and confirmation tasks can be as close as $2SI$, we observe that the sum of available time for tasks

Figure 4: The execution of the jobs issued by the search task when the jobs only run on the three selected VSP's, and $C_s = 1\frac{1}{2}SI$.

other than the search task within every two consecutive periods varies significantly. That is, the minimum sum of available time for track and confirmation tasks within every two consecutive periods is reduced. For example, the minimum sum of available time for track and confirmation tasks happens at the second and third periods (the total is only $1\frac{1}{2}SI$). On the contrary, if we pack the jobs of the search task as much as we can (on a small number of VSP's, which will be discussed later), and always assign jobs to the VSP's which are available first, then the sum of available time for track and confirmation tasks within every two consecutive periods tends to have a less fluctuation (which is no less than $4SI$), as shown in Figure 4.

As astute readers may notice, when the processing times C_s of the jobs of the search task are reduced, e.g., $C_s = 1\frac{1}{4}SI$, the situation remains. It is obvious that when the processing times C_s of the jobs of the search task is increased, e.g. $C_s = 2SI$, the minimum sum of available time for track and confirmation tasks within every two consecutive periods is reduced to zero, compared to the situation when $C_s = 1\frac{1}{2}SI$ (A similar figure can be derived from Figure 3). In other words, critical track and confirmation tasks might suffer from "transient overload" and miss their deadlines, when jobs of the search task may run on all VSP's!

When the processing time C_s of the jobs of the search task is under SI , it is clear that the minimum sum of available time for track and confirmation tasks within every two consecutive periods remains the same, regardless of whether jobs of the search task are scattered over all VSP's or not. However, we must point out that since the processing times of track and confirmation tasks often divide SI , the job packing approach still tends to provide better performance on average because track and confirmation tasks are given entire SI 's under the packing approach.

The observation in the previous paragraphs motivates a rule of thumb for task allocation in SP's called the *Job Packing Policy*, where traditionally approaches may have search jobs processed on all VSP's:

Rule 1 *All jobs of the search task should be packed on a collection of VSP's as much as possible.*

In the next section, we shall show that the well-known *earliest deadline first* (EDF) algorithm [12], which assigns a higher priority to any task with a closer deadline, is preferred in scheduling jobs of the search task over multiple VSP's. We must point out that we do not intend to claim that the above packing policy is an optimal solution in general (although some nice property with certain real-time scheduling algorithm can be proved later). The observation in previous paragraphs does suggest that the packing approach usually provides a less fluctuation in the amount of available processing time for track and confirmation tasks. We should also emphasize that the search task is the only periodic task at the SP level. With the workload separation of the search task and other tasks, the Job Packing Policy has an advantage in estimating and deriving the capacity of the system. As astute readers may notice, the above policy remains good when the ready time parameter R of the search task is not zero, where R is usually relatively small, compared to SI . Most importantly, the job packing approach provides a better way in estimating the system capability in servicing search and track tasks, which will be elaborated in later sections. For the rest of this paper, we assume that jobs of the search task are allocated by the Job Packing Policy.

4.2.2 A Three-Level Deadline-Driven Scheduling Policy

In many phased array radars, periodic search tasks, which are responsible of searching suspicious targets in the surveillance space, usually have higher priorities than track and any other tasks at both RCC and SP levels. The minimum operation requirements often focus on the schedulability of the search task. The priorities of all SP tasks can be, in general, classified in the way that the search task has the highest priority, and track tasks have the lowest priority [7].

In this section, we shall show, as follows, that the well-known *earliest deadline first* (EDF) algorithm [12], which assigns a higher priority to any task with a closer deadline, is optimal in scheduling tasks (or jobs) of the same type in a non-preemptive fashion over multiple VSP's. EDF is applied under a greedy policy in which a job (or task) is always assigned to the VSP which is assigned to the task type and is available first. We call such policy *Leveled EDF* (LEDF). The VSP assigned to a task type is called a selected VSP for the task type. Note that track and confirmation tasks can utilize the available processing time of the search-task-selected VSP's left by the search task. We can show the following properties of LEDF:

Theorem 1 *Leveled EDF is optimal in scheduling jobs of the search task over the selected VSP's in a non-preemptive fashion.*

Theorem 2 *Leveled EDF is optimal in scheduling confirmation tasks on the available processing time (left in scheduling jobs of the search task) of all VSP's in a non-preemptive fashion.*

Theorem 3 *Leveled EDF is optimal in scheduling track tasks on the available processing time (left in scheduling jobs of the search task and confirmation tasks) of all VSP's in a non-preemptive fashion.*

Figure 5: A Leveled EDF schedule when the jobs of the search task only run on selected VSP's.

Example 1 A Leveled EDF schedule

Let a SP system consist of 5 VSP's, the peak duration of the search task have 3 jobs, and the ready time R of each job of the search task be zero. Suppose that each job of the search task needs $C_s = 1\frac{1}{2}SI$ amount of processing time, as shown in Table 2. During the peak duration, the search task issues 3 jobs per SI. Outside the peak duration, the search task issues 1 job per SI. Let the processing times of a confirmation task and a track task be both equal to $C_c = C_t = \frac{1}{4}SI$.

Figure 6: A Leveled EDF schedule when the jobs of the search task may run on all VSP's.

Suppose that 9 track tasks and 2 confirmation tasks occur at the first SI, and 3 track tasks and 2 confirmation tasks occur at the second SI. Let their relative deadlines be $2SI$. Figure 5 shows the execution of the SP scheduled by the Leveled EDF algorithm when jobs of the search task only execute on the first three VSP's.

All tasks and jobs meet their deadline. For comparison, Figure 6 shows the execution of the SP scheduled by the Leveled EDF algorithm when jobs of the search task may execute on all VSP's. It was shown that one track task issued in the first SI misses its deadline at the end of the second SI. Obviously, it is due to the fluctuation of available processing time left by the search task. $\square$

Note that although Leveled EDF is optimal in scheduling each individual type of tasks (/jobs) on a multi-VSP SP, it is, in general, not an optimal scheduling algorithm in the mixed scheduling of search jobs, track tasks, and confirmation tasks. Note that Dhall [4] showed that EDF is not optimal for multiprocessor environments, and Mok [13] showed that real-time scheduling with mutual exclusion is, in general, NP-hard. We must also point out that a simple EDF policy may not be suitable in SP scheduling because the highly dynamic nature of the arrival patterns of track and confirmation tasks may result in possible violations of the radar minimum operation, which is often on the schedulability guarantee of the search task. As astute readers may point out, when an admission control mechanism is provided to manage the workload of confirmation and track tasks, the schedulability of the search task might still be guaranteed, although the system capacity estimation might become complicated. However, we must emphasize that Leveled EDF is a simple and intuitive algorithm which results in an easy estimation of the system capacity and good performance (to be illustrated later).

4.3 System Capacity Estimation

The purpose of this section is to derive the bounds on the number of VSP's needed to schedule digital signal processing under the Job Packing Policy and the Leveled EDF scheduling algorithm to satisfy the minimum operation requirements.

4.3.1 An Upper Bound

Let N be the number of internal nodes assigned to the search task $\tau^{search} = \{R, C_s, (SD \cdot SI), Max, Min, K, P\}$, where in the first K periods, the search task will request Max identical non-preemptive jobs, and each of them is of the size C_s . Starting from the $(K+1)$ period until the P_{th} period, the search task will request Min non-preemptive jobs, and each of them is of the size C_s . The search task repeats for each P periods. The relative deadline of each non-preemptive job is $(SD \cdot SI)$. When there are x non-preemptive jobs $J_1, J_2, \dots, J_x$ issued in a period, the ready time of the i_{th} job is set as $(R \cdot i)$

from the beginning of the period. We can show the following theorems:

Theorem 4 *When $C_s \leq SI$, the number of VSP's needed for the search task is less than or equal to Max .*

We must point out that Theorem 4 only provides an intuitive idea on the maximum number of VSP's needed for the search task. When $C_s = SI$ and $K = P$, the number of VSP's needed for the search task is exactly Max . When $C_s < SI$, the number of VSP's needed for the search task is, in fact, a simple variation of the well-known bin packing problem [6, 16]. Since C_s in many systems is often larger than SI , we shall focus on the case when $C_s > SI$. We refer interested readers to [6, 16] for solutions of the bin packing problem.

Suppose that the number of VSP's reserved for the search task in a SP is N , and $C_s = SI + (X \cdot R)$, where X is a positive integer. For the rest of this section, we shall consider a practical case in which $C_s \leq 2SI$, i.e., $(X \cdot R) \leq SI$, and $N < 2Max$. Let $J_{i,j}$ denote the j_{th} job of the search task issued at the i_{th} SI. Note that the ready time of j_{th} job is $(j \cdot R)$ from the beginning of its issuing SI, and $(Max \cdot R) \leq SI$ because jobs (including the Max_{th} job) issued in a SI must be ready inside the SI.

Lemma 1 *When $K = P$, $J_{i,j}$ is allocated to the $((i-1) \cdot Max + j - 1) \bmod N + 1)_{th}$ VSP.*

Lemma 2 *When $K = P$, and the number of VSP's located for the search task is $(Max + X)$, every job $J_{i,j}$ of the search task will finish no later than $(SI + (2Max + X - j) \cdot R)$ from the beginning of its issuing SI.*

Proof. The proof of this theorem comes from the observation: Job $J_{(i-2),Max}$ issued at the $(i-2)_{th}$ SI must finish no later than the time $((i-1) \cdot SI) + (Max + X) \cdot R \leq ((i-1) \cdot SI) + (X \cdot R)$ because $(Max \cdot R) \leq SI$. $\square$

Given the fact that $C_s > SI$, the relative deadline of jobs of the search task is no less than $2SI$. We can show the following theorem:

Theorem 5 *When $K = P$, the minimum number of VSP's needed for the search task is no more than $(Max + X)$.*

Note that the bound $(Max + X)$ in Theorem 5 is pretty tight when $K = P$ because every job fits in the right spot without causing any job issued in the next SI any delay in processing. If there is any bad delay, there can be a propagation of delays such that eventually some search job will miss its deadline, regardless of how far the deadline is.

Corollary 1 *When $K \leq P$, the minimum number of VSP's needed for the search task is no more than $(Max + X)$.*

4.3.2 A Lower Bound

Theorem 5 and Corollary 1 provides a good intuition for the understanding of job packing on VSP's, and an upper bound for the number of VSP's needed for the search task is provided. We can show the following theorems to derive a lower bound so that engineers may reduce the search range of the number of VSP's needed for the search task.

Theorem 6 *When $P = K$, the number of VSP's needed for the search task is no less than N if $\lfloor \frac{P \cdot Max}{N} \rfloor \cdot C_s \geq (P \cdot SI)$.*

Proof. It follows from the fact that the minimum of the processing time needed on each VSP is $\lfloor \frac{P \cdot Max}{N} \rfloor \cdot C_s$, and it must be completed within each P periods. $\square$

Theorem 7 *When $P > K$, the number of VSP's needed for the search task is no less than N if $(\lfloor \frac{K \cdot Max}{N} \rfloor + \lfloor \frac{(P-K) \cdot Min}{N} \rfloor) \cdot C_s \geq (P \cdot SI)$.*

5 Simulation Experiments

5.1 Data Set and Measurement

The experiments described in this section are meant to assess the capability of the Job Packing policy and the Leveled EDF algorithm in scheduling digital signal processing. We have implemented a simulation model for a component-oriented phased array radar SP. We compare the performance of the traditional FIFO-like scheduling mechanism (FIFO), the earliest deadline first algorithm (EDF), and the Leveled EDF algorithm with and without the Job Packing policy (abbreviated as LEDF-JP and LEDF) based on typical SP workload characteristics.

The primary performance metric is the number of VSP's, referred to as *VSPNumber*. The smaller the *VSPNumber*, the better the algorithm is. Note that a smaller number of VSP's means a better system performance, and one VSP is capable of processing a large number of track tasks.

The test data sets were generated based on typical SP workload characteristics. The number of search jobs per SI during the peak duration was 6, and the big cycle of the search task was 128 SI. (Note that since these two numbers were constants in our experiments, their values did not have any significant impact on the comparison of different scheduling algorithms.) We considered 0.2 and 0.33 as the low and upper bounds of the ratio of the peak duration in a big cycle, respectively. We set 0.25 and 0.5 as the low and upper bounds of the ratio of job numbers in the peak and normal duration. The

deadlines of each search job and each confirmation task were set as a reasonable number 6 SI. The deadlines of track tasks were generated by a random number generator in the range between 2 SI and 30 SI. 1.5 SI and 2 SI were the low and upper bounds of the processing time of a search job. 0.25 SI and 0.33 SI (/0.125 SI and 0.25 SI) were the low and upper bounds of the processing time of a confirmation (/track) task. The experiments simulated task sets with a number of tracks between 400 to 4,000, which represents a range of 4 to 40 tracks per 10 SI, where the arrival pattern of a track task has a Poisson distribution with a mean equal to 100 and a variance equal to 100. The ratio of track tasks and confirmation tasks was about 4. Each task set was simulated for 40,000 SI. 10 task sets per track workload were tested, and their results were averaged.

The simulation experiments repeated for each scheduling algorithm for the minimum number of VSP's under each given workload. If a scheduling algorithm can not schedule a given workload under a specific number of VSP's, then the number of VSP's was increased, and the same simulation repeated until the workload was schedulable.

5.2 Experimental Results: System Capacity

We considered workloads with and without confirmation tasks. Workloads without confirmation tasks were for a fully loaded phase, where no new target tracking could be afforded. Workloads with confirmation tasks were for a normal phase. Experimental results in Figures 7 and 8 considered a fully loaded phase. Figure 9 considered a normal phase. Because of limited space and similar results, other experimental results were not included here.

Figure 7.(a) and (b) show the number of needed VSP's (for LEDF-JP, LEDF, FIFO, and EDF), when the processing times C_t of a track task were equal to 0.25SI and 0.125SI, respectively. When the number of tracks per 10 SI's increased, the performance difference between real-time scheduling algorithms, such as LEDF-JP and EDF, and traditional scheduling policy FIFO increased. The performance of LEDF-JP and EDF were similar, and they were better than LEDF (which did not consider job packing), especially when the workload ratio between search jobs and tracking tasks was high (i.e., when the number of tracking tasks was small). Note that one additional VSP could much improve the capacity of the system in terms of the number of track and confirmation tasks. We must also emphasize that EDF does not consider the semantic importance of tasks in digital signal processing and might suffer from the burst of the arrivals of track and confirmation tasks.

The results shown in Figure 8 were similar to those in Figure 7, except that the processing time of a search job $C_s = 1.5SI$. Because C_s was smaller in Figure 8, the number of VSP's needed for each scheduling algorithm was smaller.

When confirmation tasks were considered, Figure 9 shows the number of needed VSP's (for LEDF-JP, LEDF, FIFO, and EDF), when the processing times C_t of a track task were equal to 0.25SI and 0.125SI, respectively. Note that the experiments in Figures 8 and 9 only differed in the consideration of confirmation tasks. Obviously, when a normal phase was considered, the advantage of the Job Packing policy was shown. Real-time scheduling algorithms still greatly outperformed the traditional FIFO-like algorithm. The performance of LEDF-JP was close to that of EDF. In general, the performance differences of simulated algorithms were similar, when C_s and C_c were larger.

We conclude that real-time scheduling algorithms did greatly improve the performance of SP, compared to the traditional FIFO-like scheduling algorithm. The Job Packing Policy improved the SP performance significantly. Note that although the improvement on the number of VSP's was small, the increased number of tracking tasks was large. Here, it was shown that LEDF-JP provided reasonable performance, compared to EDF, where EDF may not be suitable in real-time SP scheduling because it could not meet the radar minimum operation requirements.

6 Conclusion

This work is one of the first attempts in building a truly real-time SP for the next-generation phased array radars. We target the two most important issues in the design of a typical component-oriented SP: the schedulability of critical tasks and the system capacity estimation. We first formalize the workload of a component-oriented SP for modern phased array radars. We then propose a simple but effective task allocation policy, which separates periodic and aperiodic workloads, such that the number of processing units needed by a SP can be better bounded. We present a three-level EDF-based scheduling algorithm to reflect the semantic importance of tasks and to process digital signals in a real-time fashion. We also derive bounds for the number of processing units needed for a SP under performance specifications. We must emphasize that virtually everything was done empirically in the past. Although researchers have started considering real-time scheduling at the Radar Control Computer (RCC), e.g., [2, 5, 7, 10, 11], little work has been done in real-time scheduling of digital

signal processing at the SP level. Inefficient resource allocation mechanisms like FIFO were adopted in the traditional SP design, and the system capacity was very difficult to estimate or estimated very conservatively.

This work is one of the pioneer work in building the next-generation SP's, especially with real-time technology. The strength of our methodology is verified by a series of experiments, for which we have very encouraging results. Our proposed methodology has a performance close to the powerful EDF algorithm and, at the same time, follows the semantic importance of radar tasks and provides bounds on the number of VSP's needed for a SP under performance specifications. We must point out that a simple EDF policy may not be suitable in SP scheduling because the highly dynamic nature of track and confirmation tasks may result in possible violations of the radar minimum operation requirements (which is often on the schedulability guarantee of the search task). EDF with an extra admission control mechanism on confirmation and track tasks might also complicate the system capacity estimation.

For the future work, we will tune up our methodology for radar systems of different scales and goals. We will start designing a multi-SP radar system and propose methodology in integrating task scheduling at RCC and SP levels. We shall also explore mechanisms for overload management.

Acknowledgement: We would like to thank Dr. Tai-Chung Wang at III and Dr. Yu-Lin Su at the Chung Shan Institute of Science and Technology, Taiwan, for their help in this work.

References

- [1] R.A. Baugh, "Computer Control of Modern Radars," RCA M&SR-Moores-town Library, 1973.
- [2] A. Barbato and P. Giustiniani, "An Improved Scheduling Algorithm for a Naval Phased Array Radar," ALENIA Defence Systems, Italy.
- [3] C. Chang and T.-C. Wang, "Use object-oriented paradigm to design a programmable radar digital signal processor," Third Workshop on Object-Oriented Technology and Applications (OOTA' 97), September 1997.
- [4] S. K. Dhall, "Scheduling Periodic-Time-Critical Jobs on Single Processor and Multiprocessor Computing Systems," Ph.D. dissertation, University of Illinois, Urbana, 1977.
- [5] R. Filippi and S. Pardini, "An Example of Resources Management in A Multifunctional Rotating Phased Array Radar," *Real-Time Management of Adaptive Radar Systems, IEEE Colloquium*, 1990, pp. 2/1-2/3.
- [6] M. R. Garey and D. S. Johnson, "Computers and Intractability: A guide to the Theory of NP-Completeness," W. H. Freeman & Company, Publishers, San Francisco, California, 1979.
- [7] A.G. Huizing and A.A.F. Bloemen, "An Efficient Scheduling Algorithm for a Multifunction Radar," *IEEE International Radar Conference*, 1996, pp. 359-364.
- [8] A. Izquierdo-Fuente and J.R. Casar-Corredera, "Approach to Multifunction Radar Scheduling Simulation," *IEEE Telesystems Conference*, 1994, pp. 67-70.
- [9] G. V. Keuk and S. S. Blackman, "On Phased-Array Radar Tracking and Parameter Control," *IEEE Transactions*, Jan 1993, pp. 186-194.
- [10] K. Jeffay and S. Goddard, "A Theory of Rate-Based Execution," *IEEE 20th Real-Time Systems Symposium*, December 1999.
- [11] D.-I. Kang, R. Gerber, and M. Saksena, "Performance-Based Design of Distributed Real-Time Systems," *IEEE 1997 Real-Time Technology and Applications Symposium*, June 1997, pp. 2-13.
- [12] C.L. Liu and J.W. Layland, "Scheduling Algorithms for Multiprogramming in a Hard Real-Time Environment," *JACM*, Vol. 20, No. 1, January 1973, pp. 46-61.
- [13] A. K. Mok, "Fundamental Design Problems for the Hard Real-Time Environment," MIT Ph.D. Dissertation, Cambridge, MA, 1983.
- [14] A.K. Mok and D. Chen, "A Multiframe Model for Real-Time Tasks," *IEEE 17th Real-Time Systems Symposium*, December 1996.
- [15] R.L. Nevin and F.W. Schatz, "AN/APG-67 Multimode Radar Development," *IEEE International Radar Conference*, 1985, pp. 1-8.
- [16] C. Papadimitriou and K. Steiglitz, "Combinatorial Optimization: Algorithms and Complexity," Prentice-Hall, Inc., Englewood Cliffs, New Jersey, 1982.
- [17] "Rapid prototyping of Application Specific Signal Processors" (RASSP), <http://eto.sysplan.com/ETO/RASSP>.
- [18] D. Stromberg and P. Grahn, "Scheduling of Tasks in Phased Array Radar," *IEEE International Radar Conference*, 1996, pp. 318-321.
- [19] L. Sha, R. Rajkumar, and J.P. Lehoczky, "Priority Inheritance Protocols: An Approach to Real-Time Synchronization," *IEEE Transactions on Computers*, Vol. 39, No. 9, September 1990.

(a) $C_t = 0.25$ SI

(b) $C_t = 0.125$ SI

Figure 7: The ratio of the peak duration in a big cycle = 0.2, the ratio of peak and normal workload = 0.5, $C_s = 2SI$.

(a) $C_t = 0.25$ SI

(b) $C_t = 0.125$ SI

Figure 8: The ratio of the peak duration in a big cycle = 0.2, the ratio of peak and normal workload = 0.5, $C_s = 1.5SI$.

(a) $C_t = 0.25$ SI

(b) $C_t = 0.125$ SI

Figure 9: The ratio of the peak duration in a big cycle = 0.2, the ratio of peak and normal workload = 0.5, $C_s = 1.5SI$, and $C_c = 0.25SI$.